

EC-Net Supervisor



Overview

The EC-Net™ Supervisor is a software platform used in server-class applications. It makes managing all buildings at an enterprise level possible, giving facilities managers the ability to quickly respond to problems and insights to optimize their system.

The EC-Net Supervisor allows multiple Niagara-based EC-BOS series controllers, as well as other IP-based devices such as the ECLYPSE™ Connected IP and Wi-Fi products series, to be networked together. It serves real-time graphical information to standard Web-browser clients and provides server-level functions. These functions include centralized data logging/trending, archiving to external databases, alarming, system navigation, master scheduling, database management, and integration with other enterprise software applications. Also, it provides a comprehensive graphical engineering toolset for application development.

The EC-Net Supervisor operates with EC-Net™ web-based building management platform powered by the Niagara Framework®.

Features & Benefits

- Scalable licensing model for medium-sized sites with few integrations and EC-BOS-8 or IP-based controllers, up to large multi-site and remote campuses
- Integrates many automation systems including those for HVAC, lighting, energy, fire and smoke, physical access, video, and industrial/processing control
- Integrates enterprise-level applications including databases, user management, and hotel guest management
- Protects your system and data with best practice security features including role-based user and permissions management, password management (strength settings, expiration, history), encryption (TLS), certificates and electronic signatures
- Tagging and templating functions provides the foundation for organizing data, advanced searching capability and deploying systems more quickly and consistently
- Adaptive end user views are displayed using HTML5, for a consistent user experience across all web browsers and devices, including desktop, tablet and mobile

Model Selection

To order a fully functional EC-Net Supervisor, the following two components are required as a minimum: EC-Net Supervisor model (based on number of Niagara network connections), and Software Maintenance Agreement (SMA). If ordering a demo version, an SMA is not required. Refer to the [EC-Net Selection Tool](#) to calculate the required components.

EC-Net Supervisor Models

Example: EC-Net Supervisor 10

Series	Niagara Network connections
EC-Net Supervisor: Includes standard drivers.	0: 0 Niagara network connections 1: 1 Niagara network connection 2: 2 Niagara network connections 3: 3 Niagara network connections 10: 10 Niagara network connections 100: 100 Niagara network connections UNL: Unlimited Niagara network connections
EC-Net Supervisor Demo: Includes all drivers and EC-Net 4 Pro. Purchase this version for internal use, e.g. technician's laptops. Note: This license expires annually, and its renewal is covered by the EC-Net Support Fee.	N/A

For more information regarding the EC-Net drivers currently offered by Distech Controls, refer to the [EC-Net Drivers Reference Guide](#).

EC-Net Supervisor Software Maintenance Agreement

Software maintenance is required when purchasing an EC-Net Supervisor. The minimum initial software maintenance plan is 18 months. Optional 3- or 5-year maintenance may be substituted.

If Maintenance coverage is not purchased for any period, the price of Maintenance for the next period for which it is purchased will be (a) the Maintenance fee for the period(s) for which Maintenance was not purchased, up to a maximum of 5 years; and (b) the Maintenance fee for the next year.

These software maintenance plans are ordered separately according to the EC-Net Supervisor model chosen. See the price list for more details. Take advantage of the Asset Manager online tool to receive notifications about SMA expirations and Enterprise SMA to align all SMA expiration dates to a single one for the entire system.

Example: EC-Net Supervisor 10 – 5-year SMA

Series	Software Maintenance Agreement
EC-Net Supervisor 0	18-month SMA: Initial 18-month maintenance must be purchased in conjunction with initial Supervisor software 1-year SMA: 1-year maintenance (Includes new and interim releases) 3-year SMA: 3-year maintenance (Includes new and interim releases) 5-year SMA: 5-year maintenance (Includes new and interim releases)
EC-Net Supervisor 1	
EC-Net Supervisor 2	
EC-Net Supervisor 3	
EC-Net Supervisor 10	
EC-Net Supervisor 100	
EC-Net Supervisor UNL	

Core Capacity Upgrades

Core upgrades add extra Niagara connection capacity to the EC-Net Supervisor license. The following options are available:

Series	Upgrades
Niagara Connection Adder	Adds one additional Niagara connection to EC-Net Supervisor.
EC-Net Supervisor 100 Upgrade	Upgrades "small" EC-Net Supervisor (EC-Net Supervisor 0 through EC-Net Supervisor 10) to 100 Niagara connections. Will maintain any Niagara Connection Adder that were added to original license.
EC-Net Supervisor UNL	Upgrades EC-Net Supervisor 100 to unlimited Niagara connections.

Integration Packs

Integration packs add extra points capacity from IP-based devices to the EC-Net Supervisor software. The following options are available.

Example: EC-Net Supervisor Integration Pack - 2,500

Series	Connection Capacity
EC-Net Supervisor Integration Pack	<ul style="list-style-type: none">- 500: Supports up to 500 points (Standard drivers included).- 1,250: Supports up to 1,250 points (Standard drivers included).- 2,500: Supports up to 2,500 points (Standard drivers included).- 5,000: Supports up to 5,000 points (Standard drivers included).- 10,000: Supports up to 10,000 points (Standard drivers included).- 25,000: Supports up to 25,000 points (Standard drivers included).- 50,000: Supports up to 50,000 points (Standard drivers included).

Compatibility

In any given EC-Net 4 system, the EC-Net Supervisor must be running the highest version of any Niagara instance in the architecture.

When connecting to EC-BOS series controllers that are running older versions of EC-Net 4, these compatibility guidelines apply:

- EC-Net^{AX}: EC-Net Supervisors can connect to EC-BOS series controllers running EC-Net^{AX} versions 3.6.406, 3.7.108, 3.8.38 or higher.
- EC-Net R2: EC-Net^{AX} and EC-Net Supervisor can connect to an EC-BOS running R2 through the oBIX XML interface only. oBIX is included in all EC-Net^{AX} and EC-Net Supervisors as a means of integrating EC-Net-based Release 2 (R2) EC-BOS controllers. With Release 2.3.522 or higher, the oBIX driver can be added to expose all data points, schedules, trends and alarms to an EC-Net^{AX} or EC-Net 4 system. This oBIX driver is both a client and a server.

Product Specifications

The EC-Net Supervisor may run acceptably on lower-rated platforms, or may require more powerful platforms, depending on the application, number of data points integrated, data poll rate, number of concurrent users, performance expectations, etc. The following are the minimum platform requirements:

Platform Requirements

Processor	Intel® Xeon® CPU E5-2640 x64 (or better), compatible with dual and quad-core processors
Memory	6 GB minimum, 8 GB or more recommended for larger systems
Hard drive	4 GB minimum, more recommended depending on archiving requirements
Display	Video card and monitor capable of displaying 1024 x 768 pixel resolution, 1080p (1920 x 1080) minimum resolution recommended
Network support	Ethernet adapter (10/100/1000 Mb with RJ-45 connector)

Specifications subject to change without notice.

ECLYPSE, Distech Controls, the Distech Controls logo, EC-Net, Allure, and Allure UNITOUCH are trademarks of Distech Controls Inc. BACnet is a registered trademark of ASHRAE; BTL is a registered trademark of the BACnet Manufacturers Association. The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks is under license. All other trademarks are property of their respective owners.

©, Distech Controls Inc., 2015 - 2024 All rights reserved.

Global Head Office - 4205 place de Java, Brossard, QC, Canada, J4Y 0C4 - EU Head Office - ZAC de Sacuny, 558 avenue Marcel Mérieux, 69530 Brignais, France